



ACCESSORY

0300WLC

300W WIRELESS SMART LANDSCAPE CONTROL + DIMMER

The Hinkley Wireless Smart Landscape Control and Dimmer easily fits onto any Hinkley Pro Series Transformer. The Smart Control and Dimmer is fully enclosed and protected against the elements. Control two dimmable and two switching lighting zones to create customized lighting patterns for exterior spaces and landscaping. Hinkley Controllers are compatible with Variable Output LumaCORE™ Lighting Systems on the switching zones only.

DETAILS	
FINISH:	Light Gray
MATERIAL:	Composite
DIMMABLE:	DOES NOT APPLY

DIMENSIONS	
WIDTH:	3.5"
HEIGHT:	4.5"
DEPTH:	3.3
WEIGHT:	3.5lb

LIGHT SOURCE	
VOLTAGE:	12v
TRANSFORMER REQUIRED:	Yes

MOUNTING	
LEAD WIRE:	1 X 10"

SHIPPING	
CARTON LENGTH:	3.7
CARTON WIDTH:	4
CARTON HEIGHT:	4.9
CARTON WEIGHT:	1.6

PRODUCT DETAILS:

- 600w or larger transformers can use multiple controllers.
- Wet Rated
- The Hinkley App reports loading per zone and total load and can control digital trim at high and low ranges.
- 12V systems with LED bulbs consume less energy leading to lower electricity bills and a reduced carbon footprint
- Wireless landscape controller mounts to the side of any Hinkley Pro Series Transformer
- Flicker-free dimming, including low levels
- High quality composite resists rust, corrosion, and fading – ideal for harsh weather conditions
- 300w total limit for all four zones